BCH Codes

Saravanan Vijayakumaran sarva@ee.iitb.ac.in

Department of Electrical Engineering Indian Institute of Technology Bombay

October 14, 2014

BCH Codes

- Discovered by Hocquenghem in 1959 and independently by Bose and Chaudhari in 1960
- Cyclic structure proved by Peterson in 1960
- Decoding algorithms proposed/refined by Peterson, Gorenstein and Zierler, Chien, Forney, Berlekamp, Massey...
- We will discuss a subclass of BCH codes binary primitive BCH codes

Binary Primitive BCH Codes

For positive integers $m \ge 3$ and $t < 2^{m-1}$, there exists an (n, k) BCH code with parameters

- $n = 2^m 1$
- $n-k \leq mt$
- *d_{min}* ≥ 2*t* + 1

Definition

Let α be a primitive element in F_{2^m} . The generator polynomial g(x) of the *t*-error-correcting BCH code of length $2^m - 1$ is the least degree polynomial in $\mathbb{F}_2[x]$ that has

$$\alpha, \alpha^2, \alpha^3, \dots, \alpha^{2t}$$

as its roots.

Let $\varphi_i(x)$ be the minimal polynomial of α^i . Then g(x) is the LCM of $\varphi_1(x), \varphi_2(x), \dots, \varphi_{2t}(x)$.

Binary Primitive BCH Code of Length 7

- *m* = 3 and *t* < 2^{3−1} = 4
- Let α be a primitive element of F₈
- For t = 1, g(x) is the least degree polynomial in 𝔽₂[x] that has as its roots α, α²
 - α is a root of $x^8 + x$

$$x^{8} + x = x(x + 1)(x^{3} + x + 1)(x^{3} + x^{2} + 1)$$

• Let
$$\alpha$$
 be a root of $x^3 + x + 1$

• The other roots of $x^3 + x + 1$ are α^2, α^4

• For
$$t = 1$$
, $g(x) = x^3 + x + 1$

- For t = 2, g(x) is the least degree polynomial in 𝔽₂[x] that has as its roots α, α², α³, α⁴
 - The roots of $x^3 + x^2 + 1$ are $\alpha^3, \alpha^5, \alpha^6$

• For
$$t = 2$$
, $g(x) = (x^3 + x + 1)(x^3 + x^2 + 1)$

For t = 3, g(x) is the least degree polynomial in F₂[x] that has as its roots α, α², α³, α⁴, α⁵, α⁶ ⇒ g(x) = (x³ + x + 1)(x³ + x² + 1)

Binary Primitive BCH Code of Length 7

For a BCH code with parameters m and t, we have

- $n-k \leq mt$
- *d_{min}* ≥ 2*t* + 1

t	g(x)	n – k	mt	d _{min}	2 <i>t</i> + 1
1	$x^3 + x + 1$	3	3	3	3
2	$(x^3 + x + 1)(x^3 + x^2 + 1)$	6	6	7	5
3	$(x^3 + x + 1)(x^3 + x^2 + 1)$	6	9	7	7

Definition

A degree *m* irreducible polynomial in $\mathbb{F}_2[x]$ is said to be primitive if the smallest value of *N* for which it divides $x^N + 1$ is $2^m - 1$

Lemma

The minimal polynomial of a primitive element is a primitive polynomial.

Single Error Correcting BCH Codes are Hamming Codes

We will prove this for m = 3. The proof of the general case is similar.

Proof.

- Consider a BCH code with parameter m = 3 and t = 1
- Let α be a primitive element of F_8 and a root of $x^3 + x + 1$
- The generator polynomial $g(x) = x^3 + x + 1$
- The code has length 7 and dimension 4
- A polynomial $v(x) = v_0 + v_1 x + v_2 x^2 + \dots + v_6 x^6$ is a code polynomial $\iff v(x)$ is a multiple of $g(x) \iff \alpha$ is a root of $v(x) \iff v(\alpha) = 0$

$$\mathbf{v}(\alpha) = \mathbf{0} \iff \mathbf{v}_0 + \mathbf{v}_1 \alpha + \mathbf{v}_2 \alpha^2 + \mathbf{v}_3 \alpha^3 + \dots + \mathbf{v}_6 \alpha^6 = \mathbf{0}$$

Single Error Correcting BCH Codes are Hamming Codes

Proof continued.

J.				
Power	Polynomial	Tuple		
0	0	(0	0	0)
1	1	(1	0	0)
α	α	(0	1	0)
α^2	α^2	(Ò	0	1)
α^3	$1 + \alpha$	(1	1	0)
α^4	$\alpha + \alpha^2$	Ò)	1	1)
$\begin{array}{c} \alpha \\ \alpha^2 \\ \alpha^3 \\ \alpha^4 \\ \alpha^5 \\ \alpha^6 \end{array}$	$1 + \alpha + \alpha^2$	(1	1	1)
α^{6}	$1 + \alpha^2$	(1	0	1)

$$v(\alpha) = 0 \iff v_0 + v_1 \alpha + v_2 \alpha^2 + v_3 \alpha^3 + \dots + v_6 \alpha^6 = 0$$

$$\iff \begin{bmatrix} 1 & \alpha & \cdots & \alpha^6 \end{bmatrix} \begin{bmatrix} v_0 \\ v_1 \\ \vdots \\ v_6 \end{bmatrix} = 0 \iff \begin{bmatrix} 1 & 0 & 0 & 1 & 0 & 1 & 1 \\ 0 & 1 & 0 & 1 & 1 & 1 \\ 0 & 0 & 1 & 0 & 1 & 1 \end{bmatrix} \begin{bmatrix} v_0 \\ v_1 \\ \vdots \\ v_6 \end{bmatrix} = \mathbf{0}$$

Degree of Generator Polynomial

Theorem

For a binary primitive BCH code with parameters m, t and generator polynomial g(x), deg $[g(x)] \le mt$.

Proof.

- $g(x) = \text{LCM} \{ \varphi_1(x), \varphi_2(x), \varphi_3(x), \dots, \varphi_{2t}(x) \}$
- If *i* is an even integer, then $i = i'2^a$ where *i'* is odd
- $\alpha^i = (\alpha^{i'})^{2^a} \implies \alpha^i$ and $\alpha^{i'}$ have the same minimal polynomial
- Every even power of α has the same minimal polynomial as some previous odd power of α

$$g(x) = \mathsf{LCM} \{ \varphi_1(x), \varphi_3(x), \varphi_5(x), \dots, \varphi_{2t-1}(x) \}$$

• Since deg (φ_i) divides *m*, we have $n - k \le mt$

- We want to show that if the generator polynomial has roots $\alpha, \alpha^2, \cdots, \alpha^{2t}$ then $d_{min} \ge 2t + 1$
- Suppose there exists a nonzero codeword $\mathbf{v} = (v_0, v_1, \dots, v_{n-1})$ of weight $\delta \leq 2t$
- The corresponding code polynomial satisfies $\mathbf{v}(\alpha^i) = 0$ for $i = 1, 2, 3, \dots, 2t$

$$v_{0} + v_{1}\alpha + v_{2}\alpha^{2} + \dots + v_{n-1}\alpha^{n-1} = 0$$

$$v_{0} + v_{1}\alpha^{2} + v_{2}\alpha^{4} + \dots + v_{n-1}\alpha^{2(n-1)} = 0$$

$$\vdots$$

$$v_{0} + v_{1}\alpha^{2t} + v_{2}\alpha^{4t} + \dots + v_{n-1}\alpha^{2t(n-1)} = 0$$

• Let $j_1, j_2, \ldots, j_{\delta}$ be the nonzero locations in the codeword $v_{j_1}(\alpha^i)^{j_1} + v_{j_2}(\alpha^i)^{j_2} + \cdots + v_{j_{\delta}}(\alpha^i)^{j_{\delta}} = 0$ for $i = 1, 2, \ldots, 2t$

$$\begin{bmatrix} \mathbf{v}_{j_{1}} & \mathbf{v}_{j_{2}} & \cdots & \mathbf{v}_{j_{\delta}} \end{bmatrix} \begin{bmatrix} \alpha^{j_{1}} & (\alpha^{2})^{j_{1}} & \cdots & (\alpha^{2t})^{j_{1}} \\ \alpha^{j_{2}} & (\alpha^{2})^{j_{2}} & \cdots & (\alpha^{2t})^{j_{2}} \\ \alpha^{j_{3}} & (\alpha^{2})^{j_{3}} & \cdots & (\alpha^{2t})^{j_{3}} \end{bmatrix} = \mathbf{0}$$

$$\implies \begin{bmatrix} \mathbf{1} & \mathbf{1} & \cdots & \mathbf{1} \end{bmatrix} \begin{bmatrix} \alpha^{j_{1}} & (\alpha^{j_{1}})^{2} & \cdots & (\alpha^{2t})^{2t} \\ \alpha^{j_{2}} & (\alpha^{j_{2}})^{2} & \cdots & (\alpha^{j_{2}})^{2t} \\ \alpha^{j_{3}} & (\alpha^{j_{3}})^{2} & \cdots & (\alpha^{j_{3}})^{2t} \\ \vdots & \vdots & \vdots & \vdots \\ \alpha^{j_{\delta}} & (\alpha^{j_{\delta}})^{2} & \cdots & (\alpha^{j_{\delta}})^{2t} \end{bmatrix} = \mathbf{0}$$

$$\implies \begin{bmatrix} 1 & 1 & \cdots & 1 \end{bmatrix} \begin{bmatrix} \alpha^{j_1} & (\alpha^{j_1})^2 & \cdots & (\alpha^{j_1})^{\delta} \\ \alpha^{j_2} & (\alpha^{j_2})^2 & \cdots & (\alpha^{j_2})^{\delta} \\ \alpha^{j_3} & (\alpha^{j_3})^2 & \cdots & (\alpha^{j_3})^{\delta} \\ \vdots & \vdots & \ddots & \vdots \\ \alpha^{j_5} & (\alpha^{j_5})^2 & \cdots & (\alpha^{j_5})^{\delta} \end{bmatrix} = \mathbf{0}$$
$$\implies \begin{vmatrix} \alpha^{j_1} & (\alpha^{j_1})^2 & \cdots & (\alpha^{j_3})^{\delta} \\ \alpha^{j_2} & (\alpha^{j_2})^2 & \cdots & (\alpha^{j_3})^{\delta} \\ \alpha^{j_3} & (\alpha^{j_3})^2 & \cdots & (\alpha^{j_5})^{\delta} \\ \vdots & \vdots & \ddots & \vdots \\ \alpha^{j_6} & (\alpha^{j_6})^2 & \cdots & (\alpha^{j_5})^{\delta} \end{vmatrix} = \mathbf{0}$$

$$\implies \alpha^{(j_1+\dots+j_{\delta})} \begin{vmatrix} 1 & \alpha^{j_1} & \cdots & \alpha^{(\delta-1)j_1} \\ 1 & \alpha^{j_2} & \cdots & \alpha^{(\delta-1)j_2} \\ 1 & \alpha^{j_3} & \cdots & \alpha^{(\delta-1)j_3} \\ \vdots & \vdots & & \vdots \\ 1 & \alpha^{j_{\delta}} & \cdots & \alpha^{(\delta-1)j_{\delta}} \end{vmatrix} = 0$$

- $\alpha^{j_1+\cdots+j_{\delta}} \neq 0$ since α is a nonzero field element
- The determinant is a Vandermonde determinant which is not zero
- This contradicts our assumption that a nonzero codeword of weight δ ≤ 2t exists

Questions? Takeaways?